

**1T-C2-520** is a high performance converter that transforms DVI-D 720p or 1080i HD signals to HD-SDI for broadcast and professional use. An analog YPbPr or RGBHV signal can also be converted to HD-SDI. It also converts a standard analog YUV signal at 525i or 625i to SD-SDI. No scaling is performed within the unit, so the input vertical rates must be exact, per the chart below. The 1T-C2-520 is controlled via front panel buttons and an on-screen display. The unit is housed in a Desktop metal case and an optional Single/Dual Rackmount Kit is available.



## Specifications

|   |                                 |
|---|---------------------------------|
| <b>DVI-I Video Input</b>                      |                                 |
| DVI-D or RGBHV                                | 1x via DVI-I Connector          |
| <b>Component Video Input</b>                  |                                 |
| YUV or YPbPr                                  | 1x via 3x BNC Connectors        |
| <b>SD/HD-SDI Video Output</b>                 |                                 |
| SMPTE259M @ 270Mb/s,<br>SMPTE292M to 1485Mb/s | 1x via BNC Connector            |
| Video Processing                              | 24 bit, 4:4:4                   |
| Output Resolutions                            | Per table below                 |
| <b>Control Method</b>                         |                                 |
| Display                                       | On screen display               |
| Front Panel Buttons                           | Menu, Up, Down                  |
| <b>Mechanical</b>                             |                                 |
| Size (HWD)                                    | 30x200x90mm(1.2"x7.87"x3.5" )   |
| Weight (Net)                                  | 0.54 kg (1.19 lbs)              |
| <b>Environmental</b>                          |                                 |
| Operating Temperature                         | 0° to +50° C (+32° to +122° F)  |
| Operating Humidity                            | 10% to 85%, Non-condensing      |
| Storage Temperature                           | -10° to +70° C(+14° to +158° F) |
| Storage Humidity                              | 10% to 85%, Non-condensing      |
| <b>Warranty</b>                               |                                 |
| Limited Warranty                              | 5 Years Parts and Labor         |

## Key Features of the 1T-C2-520

- Full Digital Operation for SDI/HD-SDI Conversion
- Serial Digital Video Output up to 1.485Gbits/sec
- HD-SDI output resolution matches DVI input
- 525i/625i YUV converts to SD-SDI
- RS-232 Interface
- Optional Single/Dual Rackmount Kit available

## Power Requirement

External Power Supply 12VDC@1A - Locking DC

## Regulatory Approvals

Converter Unit FCC, CE, RoHS

Power Supply UL, CUL, CE, PSE, GS, RoHS

## Product Item Numbers

1T-C2-520 DVI to SDI Converter

## Accessories Included

1x Power Adapter US, UK, Euro or AU

Operations Manual

## Optional Accessories

RM-230 Single/Dual Rackmount Kit

## Notes

- (1) Resolutions not listed in the Table are not supported.
- (2) No scaling is provided so the output resolution and vertical rate will match the input signal exactly.
- (3) The output clock matches input clock with no jitter reduction, so input jitter is transferred to the output.
- (4) Video input timing must correspond to SMPTE 259M/292M timing exactly or output will not be valid.

## Input-Output Conversion Table

| Digital Video Input Signal  | Analog Video Input Signal   | Output Signal                              |
|---|---|--|
| N/A   | 525-line interlaced YUV @ 59.94Hz   | 525-line SD-SDI @ 59.94Hz                  |
| N/A   | 625-line interlaced YUV @ 50Hz  | 625-line SD-SDI @ 50Hz                     |
| 720-line progressive DVI-D<br>@ 23.98, 24, 25, 29.97, 30, 50, 59.94, 60Hz | 720-line progressive RGBHV/YPbPr<br>@ 23.98, 24, 25, 29.97, 30, 50, 59.94, 60Hz | 720p HD-SDI<br>@ same frame rate as input  |
| 1080-line progressive DVI-D<br>@ 23.98, 24, 25, 29.97, 30Hz               | 1080-line progressive RGBHV/YPbPr<br>@ 23.98, 24, 25, 29.97, 30Hz               | 1080p HD-SDI<br>@ same frame rate as input |
| 1035-line interlaced DVI-D<br>@ 59.94, 60Hz                               | 1035-line interlaced RGBHV/YPbPr<br>@ 59.94, 60Hz                               | 1035i HD-SDI<br>@ same frame rate as input |
| 1080-line interlaced DVI-D<br>@ 50, 59.94, 60Hz                           | 1080-line interlaced RGBHV/YPbPr<br>@ 50, 59.94, 60Hz                           | 1080i HD-SDI<br>@ same frame rate as input |

## Panel Drawings

